

Non-trip earth loop impedance checker



A revolutionary new socket tester with non-trip earth loop impedance. Other socket testers only tell you if the earth is connected - Martindale's E-Ze Check™ Xtra tells you how good it is!

The E-ze Check Xtra performs:

- ◆ Non-trip earth loop test
- ◆ Voltage test
- ◆ Socket test

SPECIFICATIONS

Nominal operating voltage 230 V

Frequency: 50 Hz

Non-trip Earth loop impedance ranges:

0 - 1.7 - 5 - 10 - 100 - 200 - 500 Ω

Earth loop threshold accuracy: $\pm(10\% + 0.3 \Omega)$

Voltage low indication: <195 V

Voltage high indication: >270 V

Open earth indication: >500 Ω

Dimensions: Approx 65mm x 65mm x 50mm

Weight: Approx 64g

Power supply: From mains

Power consumption: <1.6 W

Overvoltage category: Cat II / 300 V

Pollution degree: 2

E-Ze check pro kit



EZ650 E-Ze Check Pro is supplied with an IEC socket with an interchangeable 3 pin adaptor and a 3 way flying lead with croc clips allowing testing at light fittings, distribution boards and terminals. The kit is contained in a handy carry case (illustrated).

SPECIFICATIONS

Nominal operating voltage 230 V

Frequency: 50 Hz

Non-trip Earth loop impedance ranges:

0 - 1.7 - 5 - 10 - 100 - 200 - 500 Ω

Earth loop threshold accuracy: $\pm(10\% + 0.3 \Omega)$

Voltage low indication: <195 V

Voltage high indication: >270 V

Open earth indication: >500 Ω

Dimensions: Approx 65mm x 65mm x 50mm

Weight: Approx 64g

Power supply: From mains

Power consumption: <1.6 W

Overvoltage category: Cat II / 300 V

Pollution degree: 2